R16 Code No: 136BB JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD B. Tech III Year II Semester Examinations, May - 2019 DESIGN OF STEEL STRUCTURES (Common to CE, CEE) Time: 3 hours Max. Marks: 75 Note: This question paper contains two parts A and B. Part A is compulsory which carries 25 marks. Answer all questions in Part A. Part B consists of 5 Units. Answer any one full question from each unit. Each question carries 10 marks and may have a, b, c as sub questions. IS 800-2007 and steel tables are permitted: PART - A (25 Marks) Differentiate nominal diameter and gross diameter of bolt. 1.a) [2] List the various types of welded joints. b) [3] List the various types of tension members. [2] c) Evaluate the effective length of column based on end conditions. d) [3] Under what conditions should a beam be checked for shear. [2] e) f) Sketch the failure mode of laterally unsupported beams. [3] What is the minimum thickness of a plate girder when it is exposed to weather but g) accessible for painting? [2] h) What do you mean by web buckling? [3] Define end bearing in roof trusses. i) [2] What are the loads acting on the roof truss and for what load combinations the truss is to be designed. [3] PART - B (50 Marks) Identify the number of bolts required for a lap joint between two plates of size 400mm × 16mm/and 100mm × 12mm/thick so as to transmit a factored load of 150/kN using a single row of M20 bolts of grade 4.6 and grade 410 plates. [10] A tie in a truss of 2 ISA $90 \times 60 \times 10$ mm is welded on either side of 10mm gusset plate 3. through the longer legs. Design the welded joint if permissible stresses in angle and fillet welds are 150MPa and 107MPa respectively. [10] Bridge truss carries an axial pull of 500 KN. It is to be a gusset plate 20mm thick by a double cover butt joint with 20 mm diameter power driven rivets. Design an economical joint. Determine the efficiency of the joint. [10]

AG AG AG AG AG AG

Design a column with single lacing system to carry a factored axial load of 1000kN.

[10]

OR

The effective length of column is 4m. Use two channels placed toe to toe.

5.

AG AG AG AG AG AG A

