

Code No: 123BY  
**JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD**  
**B.Tech II Year I Semester Examinations, November/December - 2016**  
**ELECTROMAGNETIC FIELDS**  
**(Electrical and Electronics Engineering)**

Time: 3 Hours

Max. Marks: 75

**Note:** This question paper contains two parts A and B.  
 Part A is compulsory which carries 25 marks. Answer all questions in Part A.  
 Part B consists of 5 Units. Answer any one full question from each unit.  
 Each question carries 10 marks and may have a, b, c as sub questions.

**PART-A**

(25 Marks)

- 1.a) Write the properties of potential function. [2] ✓
- b) What is Maxwell's first law? [3] ✓
- c) Define electric dipole. [2] ✓
- d) Define Convection and conduction current densities. [3] ✓
- e) Define Magnetic field intensity. [2] ✓
- f) Write the applications of Ampere's circuital law. [3] ✓
- g) Write the vector Poisson's equation. [2] ✓
- h) What are the applications of permanent magnets? [3] ✓
- i) Define time varying fields. [2] ✓
- j) How dynamically induced EMF is produced? [3] ✓

**PART-B**

(50 Marks)

- 2.a) State and prove Gauss's law as applied to an electric field and determine the field due to an infinite line charge. ✓ [5+5]
- b) Derive Poisson's and Laplace equations starting from point form of Gauss Law. [5+5]

**OR**

- 3.a) Show that the electric field intensity at any point inside a hollow charged Spherical conductor is zero.
- b) Three point charges each 5 nC are located on the x-axis at points: -1, 0 and + 1 m in free space. (i) Find  $E$  at  $x=5$ . (ii) Determine the value and location of the equivalent single point charge that would produce the same field at very large distance. [5+5]

- 4.a) Establish the electrostatic boundary conditions for the tangential components of electric field and electric displacement at the boundary of two non dielectrics.

- b) The relative permittivity of dielectric in a parallel plate capacitor varies linearly from 4 to 8. If the distance of separation of plates is 1 cm and area of cross-section of plates is  $12 \text{ cm}^2$ , find the capacitance. Derive the formula used. [5+5]

**OR**

- 5.a) A spherical capacitor with inner sphere of radius 1.5 cm and outer sphere of radius 3.8 cm has an homogeneous dielectric of  $\epsilon = 10 \epsilon_0$ . Calculate the capacitance of the capacitor. Derive the formula used.

- b) Prove that the derivative of the energy stored in an electrostatic field with respect to volume is  $\frac{1}{2} D \cdot E$ , where D and E electric flux density and electric field intensity respectively. [5+5]

- 6.a) State and explain Biot-Savart's law and derive the expression for the magnetic field at a point due to an infinitely long conductor carrying current. P6 P6
- b) What are the limitations of Amperes current law? How this law can be modified to time varying field? [5+5]

OR

- 7.a) Derive Maxwell's second equation  $\text{div}(\mathbf{B})=0$ . ✓ P6
- b) Derive magnetic field intensity due to a square current carrying element. [5+5] ✓ P6

- 8.a) Derive the Neumann's formulae for the calculation of self and mutual inductances. P6
- b) Explain the concept of vector magnetic potentials. [5+5]

OR

- 9.a) Determine the inductance of a toroid. P6 P6 P6 ✓  $L = \frac{\mu N^2 I^2}{2\pi r}$  P6
- b) A rectangular coil of area  $10 \text{ cm}^2$  carrying a current of  $50 \text{ A}$  lies on plane  $2x + 6y - 3z = 7$  such that the magnetic moment of the coil is directed away from the origin. Calculate its magnetic moment. [5+5]

- 10.a) Explain concept of displacement current and obtain an expression for the displacement current density. P6 P6 P6 P6 P6
- b) Explain in detail about modification of Maxwell's equations for time varying fields. [5+5]

OR

- 11.a) Explain Faraday's laws of electromagnetic induction and derive the expression for induced EMF. ✓ P6
- b) Derive Maxwell's equations in integral form for time varying fields. ✓ [5+5] P6

---ooOoo---

P6	P6	P6	P6	P6	P6	P6
P6	P6	P6	P6	P6	P6	P6
P6	P6	P6	P6	P6	P6	P6
P6	P6	P6	P6	P6	P6	P6